

**DIRECTED MAXIMUM RATIO COMBINING METHODS
AND SYSTEMS FOR HIGH DATA RATE TRAFFIC**

Piu Bill Wong
17280 Clara Street
Monte Sereno, CA 95030
Citizenship: China

Shimon B. Scherzer
1648 Mariani Dr.
Sunnyvale, CA 94087
Citizenship: U.S.A.

RELATED APPLICATIONS

The present application claims priority to United States provisional patent application serial number 60/218, 905 entitled "Directed Maximum Ratio Combining Methods for High Data Rate Traffic," filed July 18, 2000, the disclosure of which is hereby incorporated herein by reference. The present application is related to co-pending and commonly assigned

5 United States patent applications serial number 08/929,638, now patent number 6,108,565, entitled "Practical Space-Time Radio Method for CDMA Communication Capacity Enhancement," filed September 15, 1997, and serial number 09/229,482 entitled "Practical Space-Time Radio Method for CDMA Communication Capacity Enhancement," filed

January 13, 1999, the disclosures of which are hereby incorporated herein by reference. The

10 present application is related to co-pending and commonly assigned United States provisional patent application serial number 60/237,951 entitled "Implementation of DMRC and Scheduling of High Rate Transmission for Uplink of CDMA Data Network," filed October 3,

2000, and concurrently filed and commonly assigned United States patent application serial number [47586-P052US-10103484] entitled "Directed Maximum Ratio Combining and Scheduling of High Rate Transmission for Data Networks," the disclosures of which are hereby incorporated herein by reference.

1
2
3
4
5
6
7
8
9
10
11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2210

TECHNICAL FIELD

The present invention relates to, and finds utility within, wireless information communications systems and, more particularly, providing increased data rates in a wireless communication system through use of techniques to reduce interference.

BACKGROUND

High-speed digital data transfers via the so called "Internet" have become ubiquitous in modern society. At the same time, the world has experienced an explosion in wireless communications technology. In well-developed countries like the United States, wireless communications, particularly cellular telephone services, have proliferated as an adjunct to the wired communication network backbone. In less developed countries, wireless communication service is being developed as a primary communications medium. A need has arisen to provide digital data wireless service at ever increasing effective data rates.

Wireless radio telecommunications systems enable many mobile stations or subscribers to connect to land-based wire-line telephone systems and/or digital Internet service providers enabling access to the World Wide Web digital information backbone. Conventional wireless air-interfaces include frequency division multiple access (FDMA), time division multiple access (TDMA), and code division multiple access (CDMA), and improvements therein.

Transfer of digital data packets differs from the transfer of digital voice information.

Full duplex (simultaneous two-way) voice communication patterns imply that the data transferred between the base station and a particular mobile are real-time and substantially equal in bandwidth. It has been noted that a total delay of 200 msec (about 2 Kbit of digital data for most speech vocoders) represents intolerable latency within a voice channel. On the other hand, for high speed data packet transfers, mobile stations appear to be far more tolerant of data transfer latencies or delays, with latencies of up to 10 seconds being encountered in current wireless data systems. While such delays appear to be tolerated by the

mobile station, the delays, attributable to relatively low effective data transfer rates, are nonetheless undesirable.

Adaptive antenna array technologies used in attempting to optimize data throughput are known. Examples of spatial diversity multiple access methods employing adaptive antenna arrays are described in United States patent numbers 5,471,647 and 5,634,199 to Gerlach et al.; an article by M.C. Wells, entitled: "Increasing the capacity of GSM cellular radio using adaptive antennas", IKE (UK) Proc. on Comm. Vol. 143, No. 5, October 1996, pp. 304-310; and an article by S. Anderson, B. Hagerman, H. Dam, U. Forssen, J. Karlsson, F. Kronstedt, S. Mazur and K. Molinar, entitled: "Adaptive Antennas for GSM and TDMA Systems", IEEE Personal Communications, June 1999, pp. 74-86, all of which are incorporated by reference.

One proposed solution, known as "CDMA/HDR", uses known techniques to measure channel data transfer rate, to carry out channel control, and to mitigate and suppress channel interference. One approach of this type is more particularly described in a paper by Paul Bender, Peter Black, Matthew Grob, Robert Padovani, Nagabhushana Sindhusayana and Andrew Viterbi, entitled: "CDMA/HDR: A Bandwidth Efficient High Speed Wireless Data Service for Nomadic Users", published by Qualcomm Corporation. The disclosure of this article is incorporated herein in its entirety.

Another proposed solution is TIA/EIA interim standard, TIA/EIA/IS-2000-2 published by Telecommunications Industry Association in August, 1999. TIA/EIA/IS-2000-2 is the physical layer standard for cdma2000 spread spectrum systems, also part of the cdma2000 standard series. cdma2000 spread spectrum systems support both voice and data communications.

In cdma2000 systems and many of the new generation personal communications systems, a dedicated pilot is introduced in the reverse link. The reverse link dedicated pilot signal is an unmodulated spread spectrum signal used to assist the base station in detecting a mobile station transmission. The reverse link dedicated pilot signal is integrated at the base station and used for at least two purposes: reverse link power control and coherent demodulation of the reverse link signals.

A reverse link power control mechanism is used to ensure that all the received dedicated pilots at the base station have the same signal to interference-plus noise ratios (SINRs). Even though the received dedicated pilots have the same SINRs, the transmitting powers of these dedicated pilots from different mobile stations can be different. The dedicated pilot transmitting powers depend on the required pilot SINR at the base station and the radio propagation channels.

A coherent demodulation mechanism is used to increase base station receiver sensitivity. It is common knowledge that in most cases coherent demodulation provides approximately 3 dB better receiver sensitivity than non-coherent demodulation. Base station receiver sensitivity is further increased by use of maximum ratio combining (MRC) methods. FIGURE 1A shows a typical base station that implements coherent demodulation and maximum ratio combining mechanisms. Signals received from a plurality of receiving elements 10 are transmitted to a corresponding one of analog receivers 12. After processing, the analog signals are converted to digital signals by analog-to-digital converters (ADCs) 14. Coherent demodulators 18 then process signals from ADCs 14 and pilot signal integration circuitry 16. The outputs of demodulators 18 are then transmitted to maximum ratio combiner 19 to output a selected signal.

Although a maximum combining mechanism with multiple antenna elements can increase the base station receiver sensitivity, it does not provide interference cancellation. (In high capacity personal communications systems, the data throughput is usually limited by interference, which is composed of inter-cell and intra-cell interference.) On the other hand, the standard interference cancellation algorithms, for example, a direct matrix inversion algorithm, require a large amount of numerical computations, making the systems either impractical or expensive to build. Thus, a hitherto unsolved need has arisen for a more efficient and practical method for sending data to a base station by a plurality of mobile stations being served without causing unacceptable interference to each other.

A need therefore exists in the art for systems and methods which optimize data throughput without explicit implementation of interference cancellation algorithms of the prior art.

SUMMARY OF THE INVENTION

The present invention is directed to a system and method in which wireless systems, such as mobile stations, transmissions are controlled to reduce interference and thereby provide increased average data rates. According to a preferred embodiment, inter-cell interference is minimized through techniques employing uneven average reverse link data rates with respect to mobile stations. Additionally or alternatively, a preferred embodiment provides minimized intra-cell interference through techniques employing selection of mobile stations having a low correlation between their array response vectors. One or more selected stations can simultaneously transmit during a packet duration with minimal intra-cell interference. Inter-cell interference can also be reduced by allowing mobile stations with lower transmitting power to transfer at a higher time average data rate than mobile stations with a higher transmitting power.

In one embodiment, the mobile stations are divided into two groups, a higher time average data rate group and a lower time average rate group. The mobile stations in the higher time average rate group preferably transmit data more often than the lower time average rate group, with each mobile station in each group transmitting at its maximum instantaneous data rate. The higher time average rate group also preferably has mobile stations with lower transmitting power. This minimizes inter-cell interference.

In another embodiment of the present invention, a first mobile station in a data queue is selected for transmission during a next time interval, although a mobile station selected for transmission during the next time interval may be selected according to other criteria, such as a mobile station having a largest amount of queued data, a mobile station having a longest delay associated with queued data, a mobile station having a particular communication

channel attribute associated therewith, and/or the like. Cross correlations of array response vectors between this first mobile station with other mobile stations in the same data rate group are preferably calculated, wherein each cross correlation is associated with two mobile stations. Preferably, mobile stations having cross correlations with the first mobile station
5 that are less than a predetermined threshold are grouped into a first group.

If there are mobile stations in this first group, the mobile station corresponding to the lowest cross correlation is preferably selected as the second mobile station for transmission, along with the first mobile station, during the next time interval. If there are additional mobile stations in the first group, cross correlations between the second mobile station and the rest of the mobile stations in the first group are preferably calculated. If there is at least one cross correlation less than the predetermined threshold, the mobile station corresponding
10 to the lowest cross correlation is preferably selected as the third mobile station for transmission, along with the first and second mobile stations, during the next time interval.

However, if there are no cross correlations less than the threshold or if there are no
15 additional mobile stations in the first group, the cross correlations between the second mobile station and the mobile stations in the other data rate group as well as the cross correlations between the first mobile station and the mobile stations in the other data rate group are preferably calculated. The calculated cross correlations are preferably analyzed to determine which, if any, mobile stations have cross correlations with respect to each of the first mobile
20 station and the second mobile station which are below the predetermined threshold.

According to a preferred embodiment, if there are no mobile stations having both cross correlations less than the predetermined threshold, only the two mobile stations are selected for transmission during the next time interval. However, if there is at least one mobile station having both cross correlations less than the threshold, a third mobile station is preferably

selected for simultaneous communication during the next time interval. Preferably, if there is more than one mobile station having both cross correlations below the threshold, the cross correlations for each mobile station is summed and the mobile station having the lowest combined cross correlations is selected selected as the third mobile station for transmission during the next time interval.

If there are no mobile stations in the first group, the cross correlations between the first mobile station with mobile stations in a second data rate group are preferably calculated. Mobile stations in the second data rate group having cross correlations less than the predetermined threshold are preferably grouped into a second group. According to a preferred embodiment, if there are no mobile stations in the second group, only the first mobile station is selected for transmission during the next interval. However, if there is one or more mobile stations in the second group, the mobile station corresponding to the lowest cross correlation is preferably selected as the second mobile station for transmission, along with the first mobile station, during the next time interval. According to a preferred embodiment, if there is only one mobile station in the second group, only the two mobile stations are selected for transmission during the next time interval.

However, if there are two or more mobile stations in the second group, cross correlations between the second selected mobile station and the rest of the mobile stations in the second group are preferably calculated. Mobile stations in the second group having cross correlations with respect to the second selected mobile station less than the predetermined threshold are preferably grouped into a third group. According to a preferred embodiment, if there are no mobile stations in the third group, no further mobile stations are selected for transmission during the next time interval. However, if there is at least one mobile station in the third group, the mobile station corresponding to the lowest cross correlation is selected as

the third mobile station for transmission, along with the first and second mobile stations, during the next time interval.

According to alternative embodiments of the invention, additional mobile stations are selected, such as through repetition of the grouping patterns outlined above, as desired. The selected mobile stations are preferably each transmitted to and/or from during the next time interval, according to the present invention.

In another embodiment, a first mobile station in the data queue is preferably selected for transmission during a next time slot, as with the previous embodiment. However, in contrast to the previous embodiment, the cross correlation of the array response vectors of the first mobile station and all the other mobile stations are preferably computed and compared to a predetermined threshold. According to this embodiment, all mobile stations with cross correlations below the threshold are candidates for selection. Preferably, if there are no such mobile stations, only the first mobile station is selected for transmission during the next time slot. However, if there is one such candidate, this candidate is preferably selected as the second mobile station, which, along with the first selected mobile station, transmits during the next time interval.

If there is more than one candidate for selection, the cross correlations of all the candidates are preferably calculated and compared to the predetermined threshold. If one or more cross correlations is below the threshold, the pair of mobile stations having the smallest combined average transmitting power are preferably selected as the second and third mobile stations for transmission, along with the first mobile station, during the next time interval. However, if there are no cross correlations below the threshold, the mobile station from the group of candidates having the smallest transmitting power is preferably selected as the

second mobile station, and only the first and second mobile stations will transmit during the next time interval.

In yet another embodiment, each of a total of N mobile stations has an associated measured response vector V . In contrast to earlier embodiments, which selected a variable number of mobile stations for each time interval (e.g., 1, 2, 3, etc. mobile stations), a fixed number L (such as 3) of mobile stations are preferably selected according to this embodiment for each of K communication time intervals. A list is preferably created in which the mobile stations that are desired for earlier selection are included more times than other mobile stations. L mobile stations are preferably selected from the list, such as randomly, and a cost function is preferably calculated by summing the cross correlations of the response vectors of the L selected mobile stations. According to a preferred embodiment, if the value of the cost function is less than the threshold, these L mobile stations are chosen to comprise the first time slot. These L mobile stations are then preferably removed from the list. However, if the value of the cost function is greater than or equal to the threshold, another L mobile stations are preferably selected from the list and their cost function is preferably calculated. According to a preferred embodiment, this processes is repeated until a cost function is calculated that is less than the threshold, at which time, the associated L mobile stations are selected and removed from the list.

If, after repeating the mobile station selection and cost function calculation process a predetermined number of times M without obtaining a cost function less than the threshold, the set of mobile stations having the smallest value cost function out of the set of M groups is preferably selected and removed from the list. These steps are preferably repeated until K groups of L mobile stations are selected for the K communication time slots.

Accordingly, a technical advantage of the present invention is provided in that optimization of data throughput is provided by selecting particular wireless communication systems for communication during a time interval, wherein each such system is preferably operated at a maximum instantaneous data rate, without explicit implementation of interference cancellation algorithms.

The foregoing has outlined rather broadly the features and technical advantages of the present invention in order that the detailed description of the invention that follows may be better understood. Additional features and advantages of the invention will be described hereinafter which form the subject of the claims of the invention. It should be appreciated by those skilled in the art that the conception and specific embodiment disclosed may be readily utilized as a basis for modifying or designing other structures for carrying out the same purposes of the present invention. It should also be realized by those skilled in the art that such equivalent constructions do not depart from the spirit and scope of the invention as set forth in the appended claims. The novel features which are believed to be characteristic of the invention, both as to its organization and method of operation, together with further objects and advantages will be better understood from the following description when considered in connection with the accompanying figures. It is to be expressly understood, however, that each of the figures is provided for the purpose of illustration and description only and is not intended as a definition of the limits of the present invention.

BRIEF DESCRIPTION OF THE DRAWINGS

For a more complete understanding of the present invention, reference is now made to the following descriptions taken in conjunction with the accompanying drawing, in which:

FIGURE 1A shows a typical base station that implements coherent demodulation and maximum ratio combining mechanisms;

FIGURE 1B shows a base station adapted according to a preferred embodiment of the present invention;

FIGURE 2 shows an illustrative data queue at successive time periods for one embodiment of the present invention;

FIGURES 3A and 3B are portions of a flow chart illustrating one embodiment of the present invention;

FIGURE 4 shows an illustrative data queue at successive time periods for the embodiment of FIGURES 3A and 3B;

FIGURE 5 is a flow chart illustrating another embodiment of the present invention; and

FIGURE 6 shows an illustrative data queue at successive time periods for the embodiment of FIGURE 5.

Wherein use of the same or similar reference numbers in different figures indicates same or like elements.

DETAILED DESCRIPTION

Preferred embodiments of the present invention minimize inter-cell interference through uneven average reverse link data rates experienced by the mobile stations and minimize intra-cell interference without explicit implementation of an interference cancellation algorithm, through choosing the mobile stations that have low correlation between their array response vectors, hence maximizing the reverse link data throughput. Array response vectors of the preferred embodiment provide information with respect to a wireless communication signal as received at or provided to antenna elements of an antenna array, such as an antenna array having a plurality of antenna elements disposed in a predetermined geometry suitable for use in beamforming by applying beamforming weighting (phase and/or amplitude) with respect to signals of antenna elements of the array. Methods and structures for providing rapid beamforming for both uplink and downlink channels using adaptive antenna arrays are described in the above referenced United States patent applications entitled "Practical Space-Time Radio Method for CDMA Communication Capacity Enhancement".

For a given instantaneous reverse link data rate, such as in cdma2000, HDR, and GSM systems for example, different mobile stations at different locations and moving conditions (hence different radio propagation channels) have different transmitting powers. The worse the radio propagation channels (i.e., the higher the power attenuation in the channel), the higher will be the mobile station transmitting power.

One method to minimize the inter-cell interference according to the present invention is to allow the lower transmitting power mobile stations to transfer a higher time average data

rate than the higher transmitting power mobile stations. For example, by assigning more time slots in a transmission time interval to the lower transmitting power mobile stations transmitting at a maximum instantaneous data rate and assigning fewer time slots in the transmission time interval to the higher transmitting power mobile stations transmitting at the maximum instantaneous data rate, the lower transmitting power mobile stations will be provided a higher time average data rate while the higher transmitting power mobile stations are provided a lower time average data rate.

According to a preferred embodiment of the present invention, a highest time average data rate is N times that of a lowest time average data rate, and the instantaneous data rate for each mobile station is kept at a possible maximum, M , where N might be from about 3 to about 9, while M may be about 150 Kbps for cdma2000 and 300 Kbps for HDR, for example. For a given N and M , in order to minimize the overall mobile stations' transmitting power according to a preferred embodiment of the present invention, the mobile stations are preferably divided into groups, such as a higher time average data rate group of mobile stations associated with the highest time average data rate and a lower time average data rate group of mobile stations associated with the lowest time average data rate. Preferably the groupings of mobile stations are selected so as to achieve a lowest average transmit power level with respect to the total number of mobile stations transmitting, e.g., mobile stations requiring a higher transmit power level are associated with the lower time average data rate group and mobile stations operating with a lower transmit power level are associated with the higher time average data rate group with the delineation between the two groups being a function of minimizing the average power associated with the mobile stations' transmissions.

If all the mobile stations are allowed to transmit only at the highest instantaneous data rate, then the aforementioned higher time average data rate mobile stations will transmit N

times more often, or N times longer, than the aforementioned lower time average data rate mobile stations. Accordingly, it should be appreciated that in such an embodiment the ratio of the time average data rates of the aforementioned higher time average data rate group and the lower time average data rate group is N.

For an example, assume that there are total of K mobile stations in a particular cell or a sector of a cell, all of which have data to transmit. The transmitting power required to transmit the highest instantaneous data rate for the k^{th} mobile station may be denoted as P_k .

Without loss of generality, it can be assumed that $P_1 \leq P_2 \leq \dots \leq P_K$. After dividing the K mobile stations into two different data rate groups, e.g., the aforementioned higher time average data rate group and lower time average data rate group, and allowing only one mobile station to transmit at a time, the overall average mobile stations' transmitting power is given below by equation (1).

$$AP = \frac{N \cdot \sum_{k=1}^J P_k + \sum_{k=J+1}^K P_k}{(N-1) \cdot J + K} \quad (1)$$

It should be appreciated that in equation (1), J is between 1 and K, inclusively, and delineates the mobile stations of the higher time average data rate group and the mobile stations of the lower time average data rate group. As discussed above, J is preferably selected so that AP (the average power) is minimum for a given P_k . By reducing the average power associated with the K mobile stations, inter-cell interference is minimized according to the present invention.

Preferred embodiments of the present invention provide for increased data capacity communications. For example, according to a preferred embodiment multiple mobile stations, such as multiple ones of the aforementioned K mobile stations in a cell or a sector of

a cell, are allowed to transmit data simultaneously to thereby provide data capacity increases above that associated with the above described one mobile station at a time transmitting. However, it should be appreciated that, if more than one mobile station in such a cell or sector is allowed to transmit simultaneously to a base station, the transmissions of these other mobile stations will likely cause intra-cell interference.

Explicit implementation of an interference cancellation algorithm, such as a directed matrix inversion algorithm, can help to reduce intra-cell interference by removing interfering signal components from a received signal. However, such interference cancellation algorithms are typically processor intensive and, thus, difficult and/or expensive to implement.

Accordingly, preferred embodiments of the present invention proactively minimize intra-cell interference by allowing only those mobile stations that have low correlations between their array response vectors to transmit data at the same time. For example, by modifying receiver architecture that implements a maximum ratio combining (MRC) algorithm, such as that shown in FIGURE 1A, preferred embodiments of the present invention may operate to identify those mobile stations having low array response vector correlation and control communication such that only those mobile stations that have an array response vector correlation below a predetermined threshold to transmit simultaneously. Minimizing intra-cell interference in this manner is referred to herein as directed MRC (DMRC). A base station adapted according to a preferred embodiment of the present invention is shown in FIGURE 1B having cross correlation estimators 101 coupled to scheduler 102 to implement DMRC according to the present invention.

The following example illustrates a preferred embodiment implementation of DMRC, with a maximum number of simultaneously transmitting mobile stations of 3. Assuming that

K=5, J=3, N=3, and all the 5 mobile stations have continuous data streams to be transmitted at the maximum instantaneous data rate, then the data queue of these 5 mobile stations may look like data queue 200 shown in FIGURE 2. Specifically, data queue 200 shows 11 data packets, U, associated with 5 mobile stations, mobile stations 1-5. The duration of data packets U shown in FIGURE 2 are on the order of 50 ms according to a preferred embodiment, although other data packet durations and even data packets of varying durations may be accommodated according to the present invention.

The data packet designators of FIGURE 2 are in the form U_ki, wherein k is a mobile station index and i is a packet index. More specifically, mobile station 1 has data packets U₁₁, U₁₂, and U₁₃ associated therewith, mobile station 2 has data packets U₂₁, U₂₂, and U₂₃ associated therewith, mobile station 3 has data packets U₃₁, U₃₂, and U₃₃ associated therewith, mobile station 4 has data packet U₄₁ associated therewith, and mobile station 5 has data packet U₅₁ associated therewith. Accordingly, the first data packet of data queue 200 waiting to be transmitted is data packet U₁₁ from mobile station 1 with packet index of 1. It should be appreciated, however, that the data packets of queue 200 are exemplary and the present invention is not limited to the illustrated number of mobile stations for which data packets are queued, the illustrated number of data packets queued, or the illustrated distribution of data packets among the mobile stations.

Assume the cross correlations between the 5 exemplary mobile stations' normalized array response vectors (ARVs), such as may be determined using cross correlation estimators of FIGURE 1B, are as shown in Table 1 below.

Mobile Station Index	Mobile Station Index	Cross Correlation (dB)
1	2	-12
1	3	-6

1	4	-19
1	5	-2
2	3	-15
2	4	-6
2	5	-21
3	4	-1
3	5	-9
4	5	-11

Table 1

Wherein the cross correlation values of Table 1 are given in dB (20 times the log based 10 of the complex modulus of the normalized ARVs cross correlations).

For example, the array response vector of each mobile station may be measured by integrating its reverse link dedicated pilot for a specific integration interval, which can vary from a fraction of a millisecond to a few tens of milliseconds. The array response vector of each mobile station may preferably be normalized, such as to a unitary vector magnitude, for cross correlation. Each combination of two mobile stations' array response vectors may then be cross correlated to provide correlation values such as shown in Table 1.

In order for multiple mobile stations to simultaneously transmit high data rate to the base station according to a preferred embodiment of the present invention, the simultaneously transmitting mobile stations' signals should not cause excessive or intolerable interference with respect to one another. Array response vector cross correlation of the present invention provides an indication of the level of interference associated with simultaneous transmission by each combination of the mobile stations. For example, if the cross correlation is less than a predefined threshold, such as -10 dB or some other value determined to be associated with an acceptable level of interference, then the mobile stations may be operated according to the present invention to simultaneously transmit high data rates, such as under control of scheduler 102 of FIGURE 1B.

A preferred embodiment method for determining mobile stations which can simultaneously transmit reverse link data in the next packet duration (e.g., frame time slot) is shown in the flowchart of FIGURES 3A and 3B. In order to more easily understand the concepts presented by the exemplary flowchart of FIGURES 3A and 3B, in addition to the assumptions with respect to the exemplary embodiment discussed above, it is also assumed that the radio propagation environment is static so the correlation of all the array response vectors are static as shown in Table 1. However, it should be appreciated that in particular implementations, such as the highly mobile environment of cellular telephony communications, the array response vectors would change appreciably with time. Accordingly, in such an embodiment the flowchart of FIGURES 3A and 3B might return periodically to the illustrated cross correlation steps, such as every packet duration, every transmission frame, or every transmission super frame, to update the cross correlations accordingly.

It should be noted that the following description describes selection of three or less mobile stations. However, such an embodiment is for illustrative purposes and is not intended to be limiting with respect to the number of mobile stations which may be selected for simultaneous transmission according to the present invention. Thus, more than three mobile stations can be selected utilizing the aspects of the present invention.

At step 300 of FIGURE 3A, the mobile stations have preferably already been identified with data rate groups, such as the higher data rate group and lower data rate group discussed above. In the embodiment of FIGURE 3A, the first mobile station having data in the data queue is preferably selected as the first mobile station for data transmission during the next time interval in step 300. The selected mobile station and its corresponding data rate

group, e.g., data rate group 1 which may be one of the above described higher time average data rate group or lower time average data rate group, for example, are preferably identified.

At step 302, the cross correlations between the first mobile station and the remaining mobile stations in data rate group 1 are calculated. Mobile stations in the data rate group 1 that have cross correlations less than a predefined threshold, CC_t , are selected as mobile stations in a new group, e.g., simultaneous transmission candidate group A, in step 304.

If there are mobile stations in data rate group 1 having cross correlations less than CC_t , i.e., mobile stations for simultaneous transmission candidate group A, as determined in step 306, the mobile station in group A with the lowest cross correlation is selected as the second mobile station for data transmission during the next time interval in step 308, i.e., the first and second mobile stations are selected for simultaneous transmission. If there are further mobile stations in group A, as determined in step 310, the cross correlations of the second mobile station with the rest of the mobile stations in group A are calculated in step 312. In step 314, the lowest cross correlation calculated in step 312 is selected and compared with threshold CC_t in step 314. If this cross correlation is less than CC_t , the mobile station corresponding with the cross correlation is selected as the third mobile station for data transmission during the next time interval in step 326, i.e., the first, second, and third mobile stations are selected for simultaneous transmission. In step 328, the three selected mobile stations are notified to prepare for to transmit data during the next packet duration.

However, if, as determined in respective steps 310 or 316, there are no other mobile stations in group A or the cross correlation selected in step 314 is greater than or equal to CC_t , the cross correlations of the second mobile station with the mobile stations in another data rate group, e.g., data rate group 2 which may be the other one of the above described higher time average data rate group or lower time average data rate group, for example, are

calculated and the cross correlations of the first mobile station with the mobile stations in this other data rate group are calculated in step 318. After selecting the users of this other data rate group having cross correlations with respect to the first user and the second user each less than CC_t as group C in step 320, it is determined if there are any users in group C in step

322. If there are no users in group C, only the first two selected mobile stations determined in steps 300 and 308 are chosen to transmit data during the next time interval, in step 324, and these two mobile stations are notified to prepare for data transmission during the next packet duration. However, if there are users in group C, the cross correlations with respect to the first user and the second user for each user of group C are summed and the user of group C with the lowest summed cross correlations is selected in step 325. The mobile station selected in step 325 is selected as the third mobile station for data transmission during the next time interval in step 326. These three mobile stations are then notified in step 328 to prepare for data transmission during the next packet duration.

If, after selecting the first mobile station in step 300, there are no other mobile stations in data rate group 1 having cross correlations less than threshold CC_t , the cross correlations of the first mobile station with the mobile stations in another data rate group, e.g., data rate group 2, for example, are calculated in step 330 of FIGURE 3B. All mobile stations in data rate group 2 having cross correlations less than threshold CC_t are selected as mobile stations in a new group, e.g., simultaneous transmission candidate group B, in step 332. If there are no mobile stations in group B, as determined in step 334, only the first mobile station is instructed, in step 336, to transmit data during the next time interval. However, if there are mobile stations in group B, the mobile station having the lowest cross correlation is selected, in step 338, as the second mobile station for data transmission during the next time interval. If this is the only mobile station in group B, as determined in step 340, the two selected

mobile stations are instructed in step 342 to prepare to transmit data during the next packet duration.

If there is more than one mobile station in group B, the cross correlations of the second mobile station (selected in step 338) with the rest of the mobile stations in group B are calculated in step 344. The lowest cross correlation as between the second mobile station and the mobile stations of group B is selected in step 346 and compared with threshold CC_t in step 348. If this cross correlation is greater than or equal to CC_t , only the first two selected mobile stations determined in steps 300 and 338 are chosen to transmit data during the next time interval, step 350, and the first and second mobile stations are instructed to prepare to transmit data during the next packet duration. However, if this cross correlation is less than CC_t , the mobile station corresponding to this cross correlation is selected in step 352 as the third mobile station for data transmission during the time interval. The three selected mobile stations are then instructed, in step 354, to prepare for data transmission during the next packet duration.

After the selected mobile stations (one, two, or three in this example) have finished transmitting for one packet duration, their new data packets will preferably be added to the end of the queue. Accordingly, operation of the above preferred embodiment method will provide data communication for all mobile stations as the steps of the method are repeated.

After implementing the above discussed preferred embodiment method of FIGURES 3A and 3B with 5 mobile stations having channel characteristics as set forth in Table 1, queued data as shown in queue 200 of FIGURE 2, and $CC_t = -10$ dB, the queued data may be removed from the queue for transmission as shown in FIGURE 4, wherein time progresses along the vertical axis. For example, during the first time interval, data packets U11 and U21 of queue 200 (shaded in FIGURE 4) are transmitted, resulting in queue 401. Repeating the

steps of FIGURES 3A and 3B, data packets U12 and U22 of queue 401 are transmitted during the second packet duration. Similarly, data packets U13 and U23 of queue 402 are transmitted during the third packet duration, data packets U31 and U24 of queue 403 are transmitted during the fourth packet duration, data packets U32 and U25 of queue 404 are transmitted during the fifth packet duration, data packets U33 and U26 of queue 405 are transmitted during the sixth packet duration, data packets U41 and U51 of queue 406 are transmitted during the seventh packet duration, and data packets U14 and U26 of queue 407 are transmitted during the eighth packet duration. Accordingly, data communication needs of each of the mobile stations are served according to the preferred embodiment method while data capacity is increased through simultaneous transmission scheduling with minimum intra-cell interference.

It should be appreciated, in the example illustrated in FIGURE 2, that entry of data packets associated with particular mobile stations has been controlled according to a preferred embodiment of the present invention. Specifically, as discussed above, it is desirable to reduce inter-cell interference and, according to a preferred embodiment of the present invention, inter-cell interference may be controlled through the providing of a higher time average data rate to mobile stations transmitting at a lower power level and providing a lower time average data rate to mobile stations transmitting at a higher power level. Accordingly, although each of the 5 mobile stations are assumed to have continuous data streams, data packets associated with mobile station 1, mobile station 2, and mobile station 3, each of which has been determined to be associated with the higher time average data rate group as described herein, are placed in queue 200 three times (i.e., $N=3$) more often than data packets associated with mobile station 4 and mobile station 5, each of which has been determined to be associated with the lower time average data rate group as described herein.

Accordingly, operation of the preferred embodiment method as described herein scheduling data transmission from queue 200 provides inter-cell interference minimization.

However, note that the actual higher time average data rate may not be 3 times of the lower time average data rate in the above described embodiment. For example, although mobile station 4 and mobile station 5 are associated with the lower time average data rate group, these stations may be disposed in a particular position or orientation such that their communications are compatible, i.e., their cross correlations are below CC_t, with many or all other mobile stations. Accordingly, such a mobile station may be selected for communications more often than their associated time average data rate group would otherwise suggest.

In radio propagation environments likely to be experienced with actual deployments of the present invention, the array response vectors (ARVs) of the mobile stations would be expected to change with time. Accordingly, the cross correlations of the ARVs would also be expected to change. Therefore, according to a preferred embodiment of the present invention, right before selection of the next combination of transmitting packet(s) according to the steps set forth above, the cross correlations between all the mobile stations are preferably updated.

Assuming one ARV of each mobile station is generated every millisecond and there are L new ARVs since the last update, then the cross correlation (CC) between mobile station i and mobile station j can be defined as shown in equation (2) below.

$$CC_{ij} = 10 \cdot \log \left(\frac{\sum_{l=1}^L |ARV_{il} \cdot ARV_{jl}|^2}{L} \right) \quad (2)$$

It should be appreciated that $| \cdot |$ is the complex modulus function and $'$ is the complex conjugate transpose function. L can be approximately the ratio of the packet duration and the ARV integration period.

Another preferred embodiment method to minimize inter-cell interference and intra-cell interference is described by the flowchart shown in FIGURE 5. In step 500, the first mobile station in the queue is selected and set as the first mobile station for data transmission. The cross correlations of the first mobile station with the rest of the mobile stations are calculated in step 502. Mobile stations having cross correlations less than a predefined threshold CCt are selected in step 504 as mobile stations for a first group of simultaneous transmission candidates (group A). If there are not any mobile stations in group A, as determined in step 506, only the first mobile station is instructed, in step 508, to transmit data during the next time interval. However, if there is only one mobile station in group A, as determined in step 510, the one mobile station is selected in step 512 as the second mobile station for data transmission during the next time interval, i.e., the first and second mobile stations are selected for simultaneous transmission. The two selected mobile stations are then instructed, in step 514, to prepare to transmit data during the next packet duration.

If there are more than one mobile station in group A, the cross correlations between all the mobile stations in group A are calculated in step 516. In step 518, all pairs of mobile stations that have cross correlations less than CCt are selected as a second group of simultaneous transmission candidates (group B). If there are no pairs of mobile stations in group B, as determined in step 520, the mobile station in group A having the lowest transmitting power is selected in step 522, and this mobile station is set as the second mobile station for data transmission during the next time interval. The first and second selected mobile stations are then instructed, in step 514, to prepare to transmit data during the next

packet duration. However, if there is at least one pair of mobile stations in group B, the pair that has the lowest combined average transmitting power is selected, in step 524, as the second and third mobile station for data transmission during the next time interval, i.e., the first, second, and third mobile stations are selected for simultaneous transmission. The three selected mobile stations are instructed to prepare for data transmission during the next packet duration in step 526. After the chosen mobile stations have finished transmitting for one packet duration, their new packets will preferably be added to the end of the queue.

To illustrate operation of this preferred embodiment method, the example assumptions as described above with respect to the method of FIGURES 3A and 3B are used with the method of FIGURE 5, except that N is now 1. Again, in order to simplify the concepts illustrated in the example, it is assumed that the radio propagation environment is static so the correlation of all the ARVs is also static as shown in Table 1. However, the transmitting powers of all the mobile stations are taken into account in determining which mobile stations can transmit reverse link data in the next packet duration. Example relative power levels that are required with respect to the 5 exemplary mobile stations to transmit at the highest data rate are shown in Table 2 below.

Mobile station Index	Relative Mobile station Transmitting Power (W)
1	1
2	0.1
3	2
4	0.01
5	10

Table 2

For example, in HDR, the relative levels of the transmitting powers of all the mobile stations, as shown in Table 2, can be estimated from the reverse link power control process and the data rate control channel in the reverse link.

It should be appreciated that in particular implementations, such as the highly mobile environment of cellular telephony communications, the radio propagation channels, and therefore the array response vectors and/or relative levels of the transmitting powers, would change appreciably with time. Accordingly, the information of Table 1 and/or Table 2 may advantageously be updated periodically. In such an embodiment the flowchart of FIGURE 5 might return periodically to the illustrated cross correlation steps and/or re-determine power levels, such as every packet duration, every transmission frame, or every transmission super frame, to update the information relied upon in operation accordingly. For example, the data of both Table 1 and Table 2 may be updated about every 5 packet durations according to a preferred embodiment.

After implementing the above discussed preferred embodiment method of FIGURE 5 with 5 mobile stations having channel characteristics as set forth in Table 1 and Table 2, queued data as shown in queue 200 of FIGURE 2, and $CCt = -10$ dB, data may be removed from the queue for transmission as shown in FIGURE 6, wherein time progresses along the vertical axis. For example, during the first time interval, data packets associated with mobile station 1 (data packets U11, U12, and U13) and mobile station 4 (data packet U41) of queue 200, as represented by the shaded user blocks of queue 601 FIGURE 6, are transmitted in a first time interval, resulting in queue 602. Repeating the steps of FIGURE 5, data packets associated with mobile station 2 and mobile station 1 of queue 602 are transmitted during a second time interval, resulting in queue 603. Similarly, data packets associated with mobile station 3 and mobile station 2 are transmitted during a third time interval resulting in queue 604, and data packets associated with mobile station 5 and mobile station 4 are transmitted during a fourth time interval. Accordingly, data communication needs of each of the mobile stations are served according to the preferred embodiment method while data capacity is

increased through simultaneous transmission scheduling with minimum intra-cell interference.

According to another preferred embodiment of the present invention, an algorithm is provided for selecting groups of mobile stations for simultaneous transmission. The members of each group are preferably controlled to transmit during a same time slot wherein their signals are separated by spatial processing of the base station beamformer. In contrast to earlier embodiments, which selected a variable number of mobile stations for each time interval (e.g., 1, 2, 3, etc. mobile stations), a fixed number L (such as 3) of mobile stations are preferably selected according to this embodiment for each of K communication time intervals.

For example, assume there is a total of N_u mobile stations, where the n th mobile station has a measured response vector $V(n)$, and there are N_s time slots available for assignment. The response vectors are assumed to be constant during the selection process. The preferred embodiment algorithm selects groups of N_g mobile stations (typically N_g is in the range of 1 to 4), where each group will be assigned a given time slot.

The preferred embodiment algorithm starts by creating a list of $N_s * N_g$ mobile stations. Each mobile station may be listed a different number of times, corresponding to the relative frequency with which that mobile station needs to be served. As a specific example, consider the case where there are $N_u = 30$ mobile stations, with a group size of $N_g = 3$, and where 10 of the mobile stations need to be served twice as frequently as the other 20. The minimum size of the list will therefore be 40 ($2 * 10 + 20$). The algorithm performs better if the list is made larger. Thus, a list size of $6 * 40 = 240$, for example, corresponds to $N_s = 240/3 = 80$ time slots.

Once the preferred embodiment list is created, Ng mobile stations are preferably selected at random off of the list. A cost function comprising of the sum of the cross correlations of the response vectors (Vs) of the mobile stations is preferably computed for the Ng selected mobile stations. For example, if Ng = 3, the cost function is preferably computed as shown below in equation (3).

$$\text{cost} = |V(n1)' * V(n2)|^2 + |V(n2)' * V(n3)|^2 + |V(n1)' * V(n3)|^2 \quad (3)$$

In equation (3) above, n1, n2, and n3 are the index numbers of the selected mobile stations, | | is the complex modulus function and ' is the complex conjugate transpose function.

If the computed cost is smaller than a specified threshold value, the Ng selected mobile stations are chosen as a group according to the preferred embodiment. If the computed cost is larger than the threshold value, another set of Ng mobile stations is randomly selected from the list, and their cost function computed. This process is preferably repeated at most N times (where N is a predetermined value). If after N trials, no set of mobile stations with sufficiently small cost has been found, the process is terminated and the set of mobile stations with the smallest cost of the N sets is chosen as a group.

Once a set of mobile stations has been chosen as a group, those mobile stations are preferably removed from the list. The above steps are preferably repeated until the list is empty, e.g., when Ns groups have been created. When the list is empty, a new list is created and the above steps are preferably again repeated.

The above-described embodiments of the present invention are merely meant to be illustrative and not limiting. It will thus be obvious to those skilled in the art that various changes and modifications may be made without departing from this invention in its broader aspects. For example, several of the embodiments are described with selection of three or less mobile stations for simultaneous transmission. However, additional mobile stations can

be selected using the present invention to reduce intra-cell interference in the reverse link. Similarly, the preferred embodiments have been discussed above with reference to mobile stations, although it should be appreciated that the present invention is not limited to use with any particular form of communication device.

5 Although the present invention and its advantages have been described in detail, it should be understood that various changes, substitutions and alterations can be made herein without departing from the spirit and scope of the invention as defined by the appended claims. Moreover, the scope of the present application is not intended to be limited to the particular embodiments of the process, machine, manufacture, composition of matter, means, 10 methods and steps described in the specification. As one of ordinary skill in the art will readily appreciate from the disclosure of the present invention, processes, machines, manufacture, compositions of matter, means, methods, or steps, presently existing or late to be developed that perform substantially the same result as the corresponding embodiments described herein may be utilized according to the present invention. Accordingly, the 15 appended claims are intended to include within their scope such processes, machines, manufacture, compositions of matter, means, methods, or steps.